



DME&JDE Hose collar

DME&JDE hose collar is composed of a stainless steel hose clamp and a polyurethane lining. It is a part of the hose whip restraining system and serves to connect the hose during operation. When the hose is under high pressure, it is prone to separating from its fitting. At this point, hose clamp can secure the hose, preventing it from randomly moving and causing injury to operators or damage to nearby equipment when the hose is under pressure.



Specification



Code	Material	ϕ MIN		ϕ MAX		Package
	Steel Grade	mm	inches	mm	inches	
DME&JDE-STOPFA11115	M6	11	433	11.5	453	10
DME&JDE-STOPFA12125	M6	12	472	12.5	492	10
DME&JDE-STOPFA13135	M6	13	512	13.5	531	10
DME&JDE-STOPFA1415	M6	14	551	15	591	10
DME&JDE-STOPFA1617	M6	16	630	17	669	10
DME&JDE-STOPFA1718	M6	17	669	18	709	10
DME&JDE-STOPFA1819	M6	18	709	19	748	10
DME&JDE-STOPFA2021	M6	20	787	21	827	10
DME&JDE-STOPFA2122	M6	21	827	22	866	10
DME&JDE-STOPFA2223	M6	22	866	23	906	10
DME&JDE-STOPFA2425	M6	24	945	25	984	10
DME&JDE-STOPFA2526	M6	25	984	26	1,024	10
DME&JDE-STOPFA2627	M6	26	1,024	27	1,063	10
DME&JDE-STOPFA2728	M6	27	1,063	28	1,102	10
DME&JDE-STOPFA2829	M6	28	1,102	29	1,142	10
DME&JDE-STOPFA3031	M6	30	1,181	31	1,220	10
DME&JDE-STOPFA3233	M6	32	1,260	33	1,299	10
DME&JDE-STOPFA3435	M6	34	1,339	35	1,378	10
STOPFLEX-STOPFA3637	M6	36	1,417	37	1,457	10
STOPFLEX-STOPFA3839	M6	38	1,496	39	1,535	10
STOPFLEX-STOPFA3940	M6	39	1,535	40	1,575	10
STOPFLEX-STOPFA4041	M6	40	1,575	41	1,614	10
STOPFLEX-STOPFA4243	M6	42	1,654	43	1,693	10

Code	Material	ϕ MIN		ϕ MAX		Package
	Steel Grade	mm	inches	mm	inches	
DME&JDE-STOPFA4344	M6	43	1,693	44	1,732	10
DME&JDE-STOPFA4445	M6	44	1,732	45	1,772	10
DME&JDE-STOPFA4547	M8	45	1,772	47	1,850	10
DME&JDE-STOPFA4850	M8	48	1,890	50	1,969	10
DME&JDE-STOPFA5153	M8	51	2,008	53	2,087	10
DME&JDE-STOPFA5354	M8	53	2,087	54	2,126	10
DME&JDE-STOPFA5456	M8	54	2,126	56	2,205	10
DME&JDE-STOPFA5759	M8	57	2,244	59	2,323	10
DME&JDE-STOPFA6062	M8	60	2,362	62	2,441	10
DME&JDE-STOPFA6365	M8	63	2,480	65	2,559	10
DME&JDE-STOPFA6668	M8	66	2,598	68	2,677	10
DME&JDE-STOPFA6971	M8	69	2,717	71	2,795	10
DME&JDE-STOPFA7274	M8	72	2,835	74	2,913	10
DME&JDE-STOPFA7577	M8	75	2,953	77	3,031	10
DME&JDE-STOPFA7880	M8	78	3,071	80	3,150	10
DME&JDE-STOPFA8183	M8	81	3,189	83	3,268	10
DME&JDE-STOPFA8486	M8	84	3,307	86	3,386	10
DME&JDE-STOPFA8789	M8	87	3,425	89	3,504	10
DME&JDE-STOPFA9092	M8	90	3,543	92	3,622	10
DME&JDE-STOPFA9395	M8	93	3,661	95	3,740	10